

### Underlag:

Belægning:	Aluminium	Messing	Bronze	Kobber	Stål	Magnesium	Rustfrit stål	Titan	Uran	Zink
Aluminium					F					
Anodisering	NF					NF				
Messing					F					
Bronze					F					
Kadmium					F					
Krom (hård)	NF ?			NF ?	F					
Krom (dekorativ)										
Kobber					F					
Eloxering	NF									
Epoxy	NF	NF	NF	NF	F		NF	NF		NF
Galvanisering					F					
Lak	NF	NF	NF	NF	F		NF			NF
Metalspray					F					
Molybdenum Disulfid					F		NF			
Nikkel (elektroplet)										
Nikkel (uden elektro)	NF ?	NF ?		NF ?	F ?					
Maling	NF	NF	NF	NF	F	NF	NF	NF	NF	NF
Plastik	NF	NF	NF	NF	F	NF	NF	NF	NF	NF
Plettering					F					
Gummi	NF				F				NF	
Resist				NF						
Rustfrit stål										
Tin					F					
Fernis	NF	NF	NF	NF	F					
Zink					F					

NF: brug umagnetisk føler

F: brug magnetisk føler

?: det er nødvendigt at kalibrere på en kendt prøve